

Блоки Питания ЭЛТИС

БП	Клеммы	Питание основных блоков	Питание э/м замка	Питание видео	Вход упр-ния	ПРИМ
PS2-C2	Y1	~15V ($\pm 10\%$) $I_H = 0,3A$				
	Y2					
PS2-C1	+U		+12V ($\pm 10\%$) $I_H = 0,6A$			
PS3-C1	-U					
PS2-CS2	Y1	~15V ($\pm 10\%$) $I_H = 0,3A$				
	Y2					
PS2-CS1	ZNC		+12V ($\pm 10\%$) $I_H \leq 0,6A$			0V по OUT
PS3-CS1	ZC (-)					
PS3-CS2	ZNO		revers			+12V по OUT
	OUT				+	
PS2-CE2	Y1	~15V ($\pm 10\%$) $I_H = 0,3A$				
	Y2					
PS3-CE1	LE-		+12V ($\pm 10\%$) $I_H \leq 0,6A$			0V по OUT
PS3-CE2	LE+					
	OUT				+	
PS2-CSD2	+U	+17V ($\pm 10\%$) $I_H = 0,8A$				
для DP201	GND					
	ZNC		+12V ($\pm 10\%$) $I_H \leq 0,6A$			0V по OUT
	ZC (-)					
	ZNO		revers			+12V по OUT
	OUT				+	
PS2-CS2D	+U	+17V ($\pm 10\%$) $I_H = 0,3A$				
для DP1	GND					
	ZNC		+12V ($\pm 10\%$) $I_H \leq 0,6A$			0V по OUT
	ZC (-)					
	ZNO		revers			+12V по OUT
	OUT				+	
PS2-DKV3	+18	+18V ($\pm 5\%$) $I_H \leq 0,5A$				
	-18					
	+13		+13V ($\pm 5\%$) $I_H \leq 0,6A$			
	-13					
	-12			+12V ($\pm 5\%$) $I_H \leq 0,6A$		
	-12					
	13S		+13V ($\pm 5\%$)			0V по OUT
	OUT				+	